

MP120UB Mini Digital Mixer Amplifier with USB & Bluetooth



Features

- Built in MP3 player, FM radio & Bluetooth with remote controller.
- Rated power 35W/120W, 70V/100V & 4-16 Ω output.
- 2 MIC input (1 6.3mm MIC & 2 XLR MIC), 1 EMC input, 2 line inputs, 1 line output.
- Built in Class-D amplifier module and switching power, with 70V/100V transformer technology.
- Individual volume control for Mic 1-3, line 1-2, MP3/FM, Bass/Treble and Master volume control.
- Support both AC100-240V & DC 24V power supply.
- Priority: EMC > MIC1 > others.
- LED indicators for power, clip, protect and signal.
- With short-circuit, clip, overload and high temp protection.
- Ideal for small venues as classroom, retail store, coffee shop, restaurant etc.

Specification

Model	MP35UB MP120UB	MP35UB MP120UB
Power Supply	~110V-240V/50/60Hz	~220V/50/60Hz
MIC1 input sensitivity	8mV±1mV	10mV±1mV
MIC2 input sensitivity	8mV±1mV	10mV±1mV
AUX1 input sensitivity	360mV±20mV	
AUX2 input sensitivity	360mV±20mV	
EMC input sensitivity	360mV±20mV	
MIC frequency response	180Hz~10kHz (±3dB)	
AUX frequency response	70Hz~16kHz (±3dB)	
Noise	<5mV (4Ω load output port)	<10mV
Distortion	<1% 1KHz	
Treble adjustment	10dB (±2)	
Bass adjustment	10dB (±2)	
Rated power supply	AC220V	
Speaker outputs	35W 4Ω, AC220V	120W 4Ω, AC220V
Interface output voltage	70V, 100V (Constant voltage output)	
Machine size(L×W×H)	247*198*66mm	
Packing size	343*302*121mm (1PC)	
Maximum packing size	630*355*283mm (4PCS)	
Net Weight	2.5kg	3Kg
Gross Weight	3.2Kg (1PC)	3.7Kg (1PC)