



DSP stereo amplifier.

D - class power ampl 30+30W @ 80hm, 50+50 @ 40hm.

Balance stereo input.

Amplifier output customisable as below:

- Linear stereo with volume adjustment for single channel, internal with trimmer or external with potentiometers (mono [Vivaldi Giove TVM](#), stereo [Vivaldi Giove TVS](#));
- Subwoofer mode with cut frequency adjustment and trimmer volume.
- Balance stereo line output for active subwoofer connection or auxiliar amp [Vivaldi MULTIMEDIA E30S](#), ##Vivaldi MULTIMEDIA E80S##;
- Possibility to select if linked to the master volume or fixed.
- The device can be set in stereo or mono mode by the dip swich on board.

Power supply 24Vdc via [Vivaldi Giove AL5B](#) (not included)

Standard DIN (6 modules)

Size (WxHxD): 106x90x63 mm

Weight 0.14 kg.

*Vivaldi srl ongoing effort to improve its products, reserves the right to make technical and aesthetic changes effectively without obligation to notice*

